

DIRECTV Gemini

Crestron Home | 1.3.19

Find the drivers in Home Setup

Add **Drivers > Cable Box > DIRECTV > Gemini Family IP Control**. Add one driver per box, enter its IP address, and enter a unique Box ID for each box. Make up your own ID, such as KITCHEN-TV. No spaces. Use a DHCP reservation or static IP address for the box.

Add **Drivers > Utility > Titan Technology > Titan Pairing Utility** on the same processor.

Compatible boxes

DIRECTV Gemini, Gemini Air, and C71-KW400 / Osprey.

Pair the box

Finish video routing and show the correct box on the TV. Open **Titan Pairing Utility** in the Home app. Select **DIRECTV** or **All**, tap **Refresh boxes**, and choose the box. Check its IP, tap **Start pairing**, enter all six TV-code characters, then tap **Pair**. Wait for **Paired** and test the source controls.

Trial and licenses

7-day trial. Purchase and assign DIRECTV licenses on the website, then use **Titan License Manager > Refresh licenses**. Titan Pairing Utility needs no separate license.

Updates and help

Update the box driver in place using **Check for Driver Update**; keep its Box ID and saved pairing. If a box is missing, check its IP and the utility filter, then Refresh boxes. For a new TV code, Cancel and Start pairing again. Use website Support if needed.

Contact Information

Titan Drivers

Installer support: TitanDrivers@protonmail.com