

Titan Pairing Utility

Crestron Home | 1.3.7

Find the utility in Home Setup

Add **Drivers > Utility > Titan Technology > Titan Pairing Utility**. In Installer Settings, choose whether its tile appears on Home, in the room, or both.

What it does

Pairs compatible Titan DIRECTV and Android TV drivers on the same Crestron Home processor. Add one utility per processor. No separate utility license is required.

Pair a box

1. Add the box driver and set its IP. Enter a unique Box ID for each box; make up your own ID, such as KITCHEN-TV. No spaces. Finish video routing and show that box on the TV.
2. Open **Titan Pairing Utility** in the Home app. Choose **DIRECTV**, **Android**, or **All**. All is the default; the dot marks the selected filter.
3. Tap **Refresh boxes**, select the box, and check its IP.
4. Tap **Start pairing**, enter all six TV-code characters (including zeroes and letters A-F), then tap **Pair**.
5. Wait for **Paired**, test the box controls, and repeat for other boxes.

Cancel or restart

Cancel stops an unfinished attempt without erasing saved pairing. **Choose box to start over** requires confirmation, clears that box's saved pairing, and requires a new TV code.

If a box is missing in the pairing utility

Select **All** in Titan Pairing Utility and tap **Refresh boxes** to see if it appears. Check the box IP address and the Box ID in the box driver settings. Use website Support if needed.

Contact Information

Titan Drivers

Installer support: TitanDrivers@protonmail.com